

KCE-300BT

Make of Phone	Type	Software Version	Bluetooth Version	Search via Phone and connect.		Search via H/U/Monitor and connect		Reconnection after ACC power off/on		Download Phonebook		Special Characters in Phonebook		Direct Number input		Dial From Phonebook		Missed calls etc		Audio Streaming		Other Comments
				Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	
Blackberry	8100	?		OK		OK		OK		NG		NG		OK		NG		NG		NG		
LG	KE970	?		OK		OK		OK		OK		NG		OK		OK		NG		NG		Bluetooth MP3 player available but A2DP not found
LG	Prada		2.0 + EDR	OK		OK		OK		NG		NG		OK		NG		NG		NG		
Motorola	Razr K1	R4527_G_08.22.07R		OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK		OK		OK		OK		NG		OK		
Motorola	Razr Maxx V6	R26117LD_U_98.20.33BR		OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK		OK		OK		OK		OK		OK		Numbers from Sim card and phone book downloaded
Motorola	Razr V3i	R479_G_08.B5.10R	v1.2	OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK		OK		OK		OK		OK		N/A		Numbers from Sim card and phone book downloaded
Nokia	5300	13.10.06/V03.92		OK		OK		OK		OK		OK		OK		OK		NG		N/A		
Nokia	6103	V 04.61, 08.02.06, RM-161	1	OK		OK		OK		NG	just 10 of 50 entires	N/A		OK		OK	just standard number	OK	Time and date 00/00/00 00:00	N/A		
Nokia	6110		2.0 + EDR	OK		OK		OK		NG		NG		OK		OK		NG		N/A		
Nokia	6131	12.05.06/V03.70		OK		OK		OK		OK		OK		OK		OK		NG		N/A		
Nokia	6230	V 03.15, 17.03.04, RH-12	1	OK		OK	after 3x	OK		NG		N/A		OK		N/A		NG	no entires	N/A		
Nokia	6230i	V 03.50		OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Nokia	6230i	V 03.81		OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Nokia	6233	V 03.70, 15.05.06, RM-145	1	OK		OK		OK		Partly	just standard numbers, for some entries characters are missing	OK		OK		OK	just standard number	OK	Time and date 00/00/00 00:00	N/A		
Nokia	6280	09-05-06/V03.81		OK		OK	Pairing took much longer	OK		OK		OK		OK		OK		NG		N/A		
Nokia	6288	07.09.06/V0592		OK		OK		OK	Unit asks if reconnection should be allowed	OK		OK		OK		OK		NG		N/A		
Nokia	6300	24.01.07/V04.70		OK		OK		OK		OK		OK		OK		OK		NG		N/A		
Nokia	6630	V6.03.08 13-02-06 RM-1		OK		OK		OK		NG		NG		OK		OK		NG		N/A		
Nokia	6680	14.04.05/V3.04.11		OK		OK	Pairing took much longer	OK		NG		NG		OK		OK		Partly		N/A		
Nokia	6310i	V 5.22, 15.11.02, NLP-1	1	OK		OK		OK		OK		OK		OK		OK		OK	Time and date 00/00/00 00:00	N/A		
Nokia	E50	Symbian OS (9.1) + Series 60 v3	2.0 + EDR	OK		NG	Finds Mobile but does not ask to connect	OK		NG		NG		OK		NG		NG		N/A		
Nokia	E61	2.0618.06.05		OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Nokia	E65	11/01/2007		OK		NG	Finds Mobile but does not ask to connect	OK		NG		NG		OK		NG		NG		N/A		
Nokia	N70	18.09.06/V5.0638.3.0.1		OK		OK	Pairing took much longer	OK		NG		NG		OK		NG		NG		N/A		
Nokia	N73	V 3.0638.0.0.1, 30.10.2006, RM-133	???	OK		OK		OK		NG	No data found	N/A		OK		N/G		N/G		N/A	No A2DP	
Nokia	N80	V4.0707.0.7		OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Nokia	N95	Symbian OS v9.2	2.0 + EDR	OK		OK		OK		NG		NG		OK		NG		NG		OK		
Samsung	D600	??	2.0 + EDR	OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Samsung	SGH720M	??	2.0 + EDR	OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Samsung	SGH-i900	??		OK		OK		OK		Partly	Not all Numbers	OK		OK		OK		NG		OK		
Samsung	SGH-U600	??		OK		OK		OK		Partly	Not all Numbers	OK		OK		OK		NG		OK		
Samsung	SGH-X630	??		OK		OK		OK		Partly	Not all Numbers	OK		OK		OK		NG		N/A		
Samsung	SGH-X820	??		OK		OK		OK		Partly	Not all Numbers	OK		OK		OK		NG		OK		
Samsung	SGH-D900	SAW V D900E.05 DEV.Version D900AMF11		OK		OK		OK		OK		OK		OK		OK		NG		NG		
Siemens	S65i	V 1.1.3		OK		OK		OK		OK	only Phonebook	OK		OK		OK		OK		N/A		
Siemens	S68	SW Vers. 38 Baseline:m75i14#main_1_0_v79.23.2		OK		OK		OK		Partly	A Few Numbers	NG		OK		OK		OK		N/A		
Sony Ericsson	M600i	Not able to check, no joystick		OK		OK		OK		OK		OK		OK		OK		NG		OK		Phone kept crashing
Sony Ericsson	p991		2.0 + EDR	OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Sony Ericsson	T610	???	1	OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Sony Ericsson	W600i	R2H002PRGCXC1250074 EU_2		OK	Pairing takes long time	OK	Pairing takes long time	OK		OK		OK		OK		OK		NG		N/A		
Sony Ericsson	W630i	R3A011PRGCXC1250487		OK		OK		OK		OK		OK		OK		OK		NG		OK		
Sony Ericsson	K750i	CXC1250035 EU_2_CL R_1CA021		OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Sony Ericsson	K800i	CXC1250210R1CB00106 0608		OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Sony Ericsson	W800i	R3A016PRGCXC1250461		OK		OK		OK		OK		OK		OK		OK		NG		OK		
Sony Ericsson	W810i	CXC1250316 R4AEA031		OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Sony Ericsson	W850i	R3A016PRGCXC1250526		OK		OK		OK		OK		OK		OK		OK		OK		OK		

Explanation of columns

Column Letter

- C: = Software version on your phone (Check Owners Manual of Telephone eg:Nokia \*#0000#)
- D: = Check which version of Bluetooth is being used, eg:Bluetooth v1.0 v1.1 v1.2 v1.2b v2.0 (Know version todate)
- E/F: = Use the phone to search for H/U/Monitor and the connection is established using your phone only.
- G/H: = Use the H/U/Monitor to search for your phone. Apart from entering the PIN number when asked there should be no other input on the phone.
- I/J: = Is the phone reconnected automatically after vehicle ACC power is turned off/on? How long does it take? 1-2minutes is ok
- K/L: = Is the phonebook downloaded?
- M/N: = Are special characters in Names displayed ok (à á etc)
- O/P: = Can you dial an entry from the Phonebook?
- Q/R: = Does the HF download the missed calls/ dialled numbers/ Received calls correctly? Can you dial them?
- S/T: = Does the HF download the missed calls/ dialled numbers/ Received calls correctly? Can you dial them?
- U/V: = If the phone supports A2DP: Go to BT-Audio source and start playing a song on your mobile. While playing change sound output to 'headphone'.Now the sound should heard over the vehicle loudspeakers. If phone does`nt support A2DP please enter N/A in this column .
- W = Here you can add other comments

TME-M740BT

Make of Phone	Type	Software Version	Bluetooth Version	Search via Phone		Search via H/U/Monitor		Reconnection after ACC power off/on		Download Phonebook		Special Characters in Phonebook		Direct Number input		Dial From Phonebook		Missed calls etc		Audio Streaming		Other Comments
				Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	Result	Notes	
BenQ Siemens	S68	38	1	OK		OK		OK		NG	No data found	NG		OK		NG		OK		N/A		
Blackberry	8100	Not able to check net info false		OK		OK		OK		NG	Numbers only no name shown	NG		OK		OK	No name shown	NG		N/A		
LG	KE970	Not able to check net info false		OK		OK		OK		NG	Numbers only no name shown	NG		OK		OK	No name shown	NG		NG		Bluetooth MP3 player available but A2DP not found.audio is given but sound breaks up all the time
Motorola	Razr K1	R4527_G_08.22.07R		OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK		OK		OK		OK		NG		OK		
Motorola	Razr Maxx V6	R26117LD_U_98.20.33BR		OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK		OK		OK		OK		OK		OK		
Motorola	Razr V3i	R479_G_08.B5.10R	v1.2	OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK	Takes long time	OK		OK		OK		NG		N/A		
Motorola	L6	R3511_G_OA.52.26R_B		OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK		OK		OK		OK		OK		N/A		
Motorola	SLVR 7	R4513_G_08.B7.DAR_RB		OK		OK	Activate the "find me" setting in the phones bluetooth menu	OK	Auto reconnection must be enabled in phone settings	OK		OK		OK		OK		OK		N/A		
Nokia	5300	13.10.06/V03.92		OK		OK		OK		OK		OK		OK		OK		NG		N/A		
Nokia	6103	V 04.61, 08.02.06, RM-161	1	OK		OK		OK		NG	just 10 of 50 entires	N/A		OK		OK	just standard number	OK	Time and date 00/00/00:00	N/A		
Nokia	6131	12.05.06/V03.70		OK		OK		OK		OK		OK		OK		OK		NG		N/A		
Nokia	6230	V 03.15, 17.03.04, RH-12	1	OK		OK	after 3x	OK		NG		N/A		OK		N/A		NG	no entires	N/A		
Nokia	6230i	V 03.50		OK		OK		OK		OK		OK		OK		OK		NG		N/A		
Nokia	6233	V 03.70, 15.05.06, RM-145	1	OK		OK		OK		Partly	just standard numbers, for some entires characters are mising	OK		OK		OK	just standard number	OK	Time and date 00/00/00:00	N/A		
Nokia	6280	09-05-06 V03.81		OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Nokia	6288	07.09.06/V0592		OK		OK		OK	Unit asks if reconnection should be allowed	OK		OK		OK		OK		NG		N/A		No connecting phone asks if you want to enable connection
Nokia	6300	24.01.07/V04.70		OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Nokia	6630	V6.03.08 13-02-06 RM-1		OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Nokia	6680	14.04.05 V3.04.11		OK		OK		OK		NG		NG		OK		NG		NG	Only Nrs dialed from 740 are shown	N/A		Numbers dialed when phone is disconnected from 740BT will not be shown or updated.
Nokia	6310i	V 5.22, 15.11.02, NLP-1	1	OK		OK		OK		OK	Timeout	Partly @ ç ñ --> OK £-->NG		OK		OK		OK	No name on display, just number	N/A	No A2DP	
Nokia	6310i	V 5.22, 15.11.02, NLP-1	1	OK		OK		OK		OK		OK		OK		OK		OK	Time and date 00/00/00:00	N/A		
Nokia	E50	Symbian OS (9.1) + Series 60 v3	2.0 + EDR	OK		NG	Finds Mobile but does not ask to connect	OK		NG		OK		OK		NG		NG		N/A		
Nokia	E61	2.0618.06.05		OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Nokia	E65	11/01/2007	?	OK		NG	Finds Mobile but does not ask to connect	OK		NG		OK		OK		NG		NG		N/A		
Nokia	N70	18.09.06/V5.0638.3.0.1		OK		OK		OK		NG		NG		OK		NG		NG		N/A		
Nokia	N73	V 3.0638.0.0.1, 30.10.2006, RM-133	???	OK		OK		OK		NG	No data found	N/A		OK		N/G		N/G		N/A	No A2DP	
Nokia	N80	V4.0707.0.7		OK		OK		OK		NG		N/A		OK		N/A				N/A		
Nokia	N95	V 11.0.026, 17.04.07, RM-159	2.0	OK		OK		OK		NG	No data found	N/G		OK		N/G		OK		OK	No A2DP	
Samsung	SGH-D900	???	???	OK		OK		OK		NG	just strange characters	N/A		OK		N/A		OK		OK		
Samsung	SGH-U600	??		OK		OK		OK		NG		NG		NG		NG		NG		NG		With direct input unit shows as being dialled but nothing happens with phone, call can not be made
Samsung	SGH-X820	??		OK		OK		OK		NG	Numbers only no name shown	NG		NG		NG		NG		OK		
Samsung	SHG-i900	??		OK		OK		OK		NG	Numbers only no name shown	NG		NG		NG		NG		N/A		With direct input unit shows as being dialled but nothing happens with phone, call can not be made
Samsung	SHG-X630	??		OK		OK		OK		NG	Numbers only no name shown	NG		NG		NG		NG				
Siemens	S65i	V 1.1.3		OK		N/G		OK		OK	only Phonebook	OK		OK		OK		N/G		N/A		
Siemens	S68	SW Vers. 38 Baseline:m7514#main_1.0 v79.23.2		OK		OK		OK		OK	Only SIM Card	NG		OK		OK		NG		N/A		
Sony Ericsson	M600i	Not able to check, has no joystick.		NG	Connects but keeps disconnecting	NG	and asking if you want to reconnect	NG		NG		NG		NG		NG		NG		N/A		Tested with other phone 740BT OK
Sony Ericsson	T610	???	1	OK		OK		OK		Partly	Numbers are incorrect +491779911 goes to 002B00340039003100370 0	NG	Will not appear in the Phone book	OK		OK		OK	No name on display, just number	N/A	No A2DP	TME-M740BT switch to different source (e.g. AUX) when hang-off the call, No name indication when receiving a call or call some number from the phonebook
Sony Ericsson	T610	???	1	OK		OK		OK		OK		OK		OK		OK		OK		N/A		
Sony Ericsson	W600i	R2H002PROCXC1250074_EU_2		NG	Connects but keeps disconnecting	NG	and asking if you want to reconnect	NG		NG		NG		NG		NG		NG		N/A		Tested with other phone 740BT OK
Sony Ericsson	W630i	R3A011PRGCXC1250487		NG	Connects but keeps disconnecting	NG	and asking if you want to reconnect	NG		NG		NG		NG		NG		NG		OK		Tested with other phone 740BT OK
Sony Ericsson	K750	CXC1250035_EU_2_CL R 1CA021		OK		OK		OK		partly	some numbers shown as ASCII	NG		OK		partly	some numbers shown as ASCII	partly	some numbers shown as ASCII	N/A		On telefon we tested there were 46 contacts only 18 contacts are downloaded and only 10 show numbers the other were shown as ASCII code
Sony Ericsson	K800i	CXC1250210R1CB0010606 08		NG		NG		NG		NG		NG		NG		NG		NG		NG		
Sony Ericsson	W800i	R3A016PRGCXC1250461		NG	Connects but keeps disconnecting	NG	and asking if you want to reconnect	NG		NG		NG		NG		NG		NG		N/A		Tested with other phone 740BT OK
Sony Ericsson	W810i	CXC1250316 R4AEA031		OK		OK		OK		OK		OK		OK		NG		NG		N/A		
Sony Ericsson	W850i	R3A016PRGCXC1250526		NG	Would not connect	OK	But does not ask for pin Nr			OK	Numbers incorrect: +491743410137 and shown is: 002B00340039003100370 0	OK		OK		OK	But numbers wrong sometimes	NG		OK		Phone number problem seems like ASCII code problem, 2B=+, 34 = 4 39 = 9, in ASCII code??

Explanation of columns

**C:** = Software version on your phone (Check Owners Manual of Telephone eg:Nokia \*#0000#)  
**D:** = Check which version of Bluetooth is being used, eg:Bluetooth v1.0 v1.1 v1.2 v1.2b v2.0 (Know version todote)  
**E/F:** = Use the phone to search for H/U/Monitor and the connection is established using your phone only.  
**G/H:** = Use the H/U/Monitor to search for your phone. Apart from entering the PIN number when asked there should be no other input on the phone.  
**I/J:** = Is the phone reconnected automatically after vehicle ACC power is turned off/on? How long does it take? 1-2minutes is okay  
**K/L:** = Is the phonebook downloaded?  
**M/N:** = Are special characters in Names displayed ok (à á etc)  
**O/P:** = Can you dial an entry from the Phonebook?  
**Q/R:** = Does the HF download the missed calls/ dialled numbers/ Received calls correctly? Can you dial them?  
**S/T:** = Does the HF download the missed calls/ dialled numbers/ Received calls correctly? Can you dial them?  
**U/V:** = If the phone supports A2DP: Go to BT-Audio source and start playing a song on your mobile. While playing change sound output to 'headphone'.Now the sound should heard over the vehicle loudspeakers. If phone does 'nt support A2DP please enter N/A in this column .  
**W** = Here you can add other comments