

Pioneer Dj

REFINED.
REMASTERED.
REBORN.

DJM-900NXS2

- 64-BIT MIXING PROCESSOR
- 96 KHZ/24-BIT SOUND CARD
- NEW EQ AND CHANNEL FADER CURVES
- IMPROVED CLIP INDICATOR
- 6 SOUND COLOUR FX WITH PARAMETER DIAL
- 14 BEAT FX WITH BIGGER X-PAD
- INDEPENDENT SEND/RETURN
- 2 USB PORTS
- 4 PHONO INPUTS
- DVS SUPPORT



Pioneer Dj

DJM-900NXS2

NUANCED SOUND, RESPONSIVE CONTROL

MAIN SPECIFICATIONS

Number of channels	4 x audio channels, 2 x MIC channels
Input ports	Digital In x 4 (coaxial), Line In x 4 (RCA), Phono x 4 (RCA), MIC x 2 (XLR & 1/4-inch TRS jack x 1, 1/4" TRS JACK x 1)
Output ports	Master Out x 2 (XLR x 1, RCA x 1), Booth Out x 1 (1/4" TRS jack), Headphone Monitor Out x 1 (1/4" stereo jack, 3.5mm stereo min-jack), Rec Out x 1 (RCA), Digital Out x 1 (coaxial)
Other ports	Send x 1 (1/4" TS jack), Return x 1 (1/4" TS jack), USB B x 2, USB A x 1, Link (LAN) x 1
Sampling rate	96kHz
D/A converter	32bit
A/D converter	24bit
Frequency response	20Hz ~ 40kHz (Line)
Total Harmonic Distortion ratio	0.005% or less (Line-Master1)
S/N ratio	105 dB (Line)
Max external dimension(W x D x H)	333 x 414.2 x 107.9 mm
Unit weight	8.0 kg

PRODUCT FEATURES



WARM, NATURAL SOUND

64-bit mixer, improved analogue input and a 96 kHz/24-bit sound card with a direct digital connection.



IMPROVED CONTROLS

Re-designed EQ and fader curves plus a more accurate clip indicator.



INDEPENDENT SEND/RETURN

Connect external devices and software and layer over on-board FX.



4 PHONO INPUTS

Connect up to 4 turntables to channels 1, 2, 3 or 4 meaning seamless DJ handovers.

